



ShurLok® Directions For Use

The ShurLok operates on a patented system of two groups of combinations. One combination opens the shackle (initial factory setting on 0-0-0-0) and the second combination opens the sliding key storage door (initial factory setting on 3-3-3-3). To change the factory default settings and to set your own combination, follow the instructions below:

1. Set dials on shackle opening combination (factory setting on 0-0-0-0) and open the shackle (to insure you are on the correct shackle opening combination)
2. Use a dime or paper clip to turn the change screw 90 degrees (1/4 turn) clock-wise to the vertical position. **Never force the change screw.** If it is difficult to turn, make sure the numbers are lined up and that you have the correct combination. If you are not on the correct shackle opening combination, the change screw will not turn.
3. Set the combination to the desired shackle combination.
4. Return the change screw to the original (horizontal) position by turning counter-clockwise 90 degrees (1/4 turn)
5. The key compartment door combination is automatically set when the new shackle combination is set. Follow the chart below to find the new combination for the sliding door.



Shackle to door conversion chart

If Shackle Is	0	1	2	3	4	5	6	7	8	9
Door Is	3	4	5	6	7	8	9	0	1	2

Example 1: Shackle combination 7724 - The door combination would then be 0057

Example 2: Shackle combination 5510 - The door combination would then be 8843

NOTES:

- Some locks are stiff being new. If the lock will not open the first time, simply press down on the dials to settle them in place.
- To change your combination again in the future, you always set the combination to your opening shackle combination prior to turning the change screw.

The ShurLok Zero Locking Feature

The ShurLok can be opened in the dark or by the vision-impaired by following the below directions:

1. Roll all numbers on the dials up and away from you. By doing so, the dials will all stop on zero.
2. Count the clicks up to your combination (Hint: if you will be using this feature often, we recommend setting your combination to lower numbers that are easier to count up to)

ShurLok Products 800-654-1786
18424 Hwy 99 FAX (206)523-9876
Lynnwood, WA 98037 www.shurlok-products.com

Patent # 381 833